

Embedded Systems



Arijit Mondal

Dept. of Computer Science & Engineering
Indian Institute of Technology Patna
arijit@iitp.ac.in

Quantitative Analysis

Introduction

- Quantitative properties
 - Position, velocity, temperature, weight, reaction time, etc.
- Execution time analysis
- Power analysis
- Need to analyze program / software
- Require models of platform


Target

- Generic problem
 - A task defined by a program P , environment E and quantity of interest q , then $q = f_p(x, w)$
 - x - input to program
 - w - environment parameters
- In most of the cases extreme value of the quantity is of interest
- Extreme case analysis: $\max_{x,w} f_p(x, w)$ or $\min_{x,w} f_p(x, w)$
- It may be difficult to determine exact value
- Threshold analysis: $\forall x, w f_p(x, w) \leq T$ or $\forall x, w f_p(x, w) \geq T$
- Average case analysis: $E_{D_x, D_w} f_p(x, w)$

Modular exponentiation: $b^e \bmod n$

```
#define EXP_BITS 32
typedef unsigned int UI;
UI modexp(UI base, UI exponent, UI mod) {
    int i;
    UI result = 1;
    i = EXP_BITS;
    while(i > 0) {
        if ((exponent & 1) == 1) {
            result = (result * base) % mod;
        }
        exponent >>= 1;
        base = (base * base) % mod;
        i--;
    }
    return result;
}
```


Control flow diagram



Modular exponentiation: $b^e \bmod n$

```
#define EXP_BITS 32
typedef unsigned int UI;
UI exponent, base, mod;
UI update(UI r) {
    UI res = r;
    if ((exponent & 1) == 1) { res = (res * base) % mod; }
    exponent >>= 1;
    base = (base * base) % mod;
    return res;
}
UI modexp_call() {
    UI result = 1; int i;
    i = EXP_BITS;
    while(i > 0) { result = update(result); i--; }
    return result;
}
```

Control flow diagram



Execution time: Loop bounds

```
for(i=EXP_BITS; i > 0; i--) {  
    if ((exponent & 1) == 1) {  
        result = (result * base) % mod;  
    }  
    exponent >>= 1;  
    base = (base * base) % mod;  
}  
  
while (exponent != 0) {  
    if ((exponent & 1) == 1) {  
        result = (result * base) % mod;  
    }  
    exponent >>= 1;  
    base = (base * base) % mod;  
}
```

Execution time: Exponential path space

```
void count() {  
    int Outer, Inner;  
    for (Outer = 0; Outer < MAXSIZE; Outer++) {  
        for (Inner = 0; Inner < MAXSIZE; Inner++) {  
            if (Array[Outer][Inner] >= 0) {  
                Ptotal += Array[Outer][Inner];  
                Pcnt++;  
            } else {  
                Ntotal += Array[Outer][Inner];  
                Ncnt++;  
            }  
        }  
    }  
}
```


Execution time: Path feasibility

```
void altitude_control_task(void) {
    if (pprz_mode == PPRZ_MODE_AUTO2 || pprz_mode == PPRZ_MODE_HOME) {
        if (vertical_mode == VERTICAL_MODE_AUTO_ALT) {
            float err = estimator_z - desired_altitude;
            desired_climb = pre_climb + altitude_pgain * err;
            if (desired_climb < -CLIMB_MAX) {
                desired_climb = -CLIMB_MAX;
            }
            if (desired_climb > CLIMB_MAX) {
                desired_climb = CLIMB_MAX;
            }
        }
    }
}
```

Execution time: Memory hierarchy


```
float dot_product(float *x, float *y, int n) {  
    float result = 0.0;  
    int i;  
    for(i=0; i < n; i++) {  
        result += x[i] * y[i];  
    }  
    return result;  
}
```

Constraints for CFG



$$\begin{aligned}x_1 &= 1 \\x_6 &= 1 \\x_1 &= d_{12} \\x_2 &= d_{12} + d_{52} = d_{23} + d_{26} \\x_3 &= d_{23} = d_{34} + d_{35} \\x_4 &= d_{34} = d_{45} \\x_5 &= d_{35} + d_{45} = d_{52} \\x_6 &= d_{26}\end{aligned}$$

Constraints for CFG



$$\begin{aligned}x_1 &= 1 \\x_6 &= 1 \\x_1 &= d_{12} \\x_2 &= d_{12} + d_{52} = d_{23} + d_{26} \\x_3 &= d_{23} = d_{34} + d_{35} \\x_4 &= d_{34} = d_{45} \\x_5 &= d_{35} + d_{45} = d_{52} \\x_6 &= d_{26}\end{aligned}$$

$$\max_{x_i, 1 \leq i \leq n} \sum_i w_i x_i$$